



MPA1260

The Omage **MPA1260** 12-channel, multi-room power amplifier is ideal for custom installations requiring up to six stereo zones. Each channel is an impressive 60 watts RMS and is stable down to 4 Ohms.

For full system control, the **MPA1260** is equipped with a global line input, individual zone line inputs, mode switches and volume controls for each channel. In this way, a source can be played through any number of channels, or specific sources may be designated to individual channels.

Built to professional standards, the **MPA1260** relies on two large toroidal transformers for a rich, full bodied sound. If greater power is required, each channel can simply be switched to bridge mono.

ROBUST TRANSFORMERS:

Two large toroidal transformers permit a rich, smooth and full bodied sound.

STATUS LIGHTS:

Six LED front-panel status lights monitor activity.

GLOBAL INPUT:

Global input enables a single source to be played in multiple zones.

LINE OUT:

Connection enables amplifiers to be daisy chained together.

12 VOLT TRIGGER:

Unit can be remotely turned on/off via a 12-volt trigger.

DETACHABLE TERMINALS:

Detachable terminals facilitate speaker wire connections.



MPA1260 - Interior View



MPA1260 - Back panel

Model	Rated output Power Stereo	Rated output Powered Bridge Mono	Total Harmonic Distortion (rated condition)	Frequency Response	Signal to Noise Ratio	Input Level	Input Impedance	Load Impedance	Power	Power Consumption	Weight Kg / lbs	Dimensions (H x W x D) mm / inches
MPA1260	12 x 60 (8 Ohm) 12 x 100 (4 Ohm)	6x120 (8 Ohm)	<1% (20Hz ~ 20 kHz)	20Hz ~ 20 kHz	> 80 dB	Stereo (4Ω): 1K/48 mV Bridged (8Ω): 1K/34 mV Stereo (4Ω): 1K/500 mV Bridged (8Ω): 1K/458 mV	47 K Ohm	Stereo 4 or 8 Ω Bridged 8 Ω	115/230v swicthable	Stereo: 228 w Bridged:377 w	35.5 / 77.2	152 x 482 x 431 / 6 x 19 x 17