



MX8 without amplifier

Hear the difference with an **Omage Spectrum** professional mixer. Portable and easy to use, the amplified 120 watts per channel **MX8-P** and the passive **MX8** both feature full-metal body construction.

When getting the right sound and mix is essential, rely on the **MX8** series. Suitable for use in recording studios, bars, restaurants with karaoke and for DJ dances and special events.

Sound shaping adjustments to control gain, highs, mids, lows, effect and pan can be made for each channel independently. Channels can also be monitored separately. All main connections are both XLR and 1/4 inch.

FEATURE:


- High-quality volume pots for smooth precise control
- Dual fan exhaust cooling to minimize heating distortion and maximize signal clarity
- Rugged full-metal body construction.



MX8-P with amplifier



XLR or 1/4 inch Inputs



Master Controls

Model	Rated output Power Stereo	Max Gain at Line Input	Total Harmonic Distortion (rated condition)	Frequency Response	Signal to Noise Ratio	Mic Impedance	Line Impedance	Tape Impedance	Return Imped.	Power	Power Consumption	Dimensions (H x W x D) mm / inches	Weight Kg / lbs
MX8	N/A	>20%	< 0.5% (40 Hz ~ 16 kHz)	20 Hz ~ 20 kHz (±1/3 dB)	> 70 dB	>1.0k Ohm	>10k Ohm	47k Ohm	20 k	~120V 60 Hz	< 30 w	63 x 381 x 348 2.5 x 15.0 x 13.7	2.8 / 6.1
MX8-P	2 X 120 w (8+8 Ohms)	>20%	< 0.5% (40 Hz ~ 16 kHz)	20 Hz ~ 20 kHz (±1/3 dB)	> 85 dB	>1.0k Ohm	>10k Ohm	47k Ohm	20 k	~120V 60 Hz	< 450 w	122 x 381 x 348 4.8 x 15.0 x 13.7	12.5 / 27.5