

MULTI-ROOM STEREO SPEAKER SELECTORS

The **AT4V** and **AT6V** speaker selectors are equipped with independent volume controls for each pair of loudspeakers. Each speaker set also has a designated A/B source selector and an On/Off switch. In this way, any combination of speakers and sources can be played through any or all outputs simultaneously. Both selectors are rated at 100w RMS per channel, while autotransformer impedance technology ensures that amplifiers will not be damaged by lower impedance levels. Push-pin connectors located on the back panels will accommodate up to 14-gauge speaker wire.

Both **AT4** and **AT6** enable switching from two sources to as many as four or six pairs of speakers that can be played simultaneously. The selectors feature independent On/Off speaker switching and are rated at 100 watts RMS per channel. To protect your audio components, they are equipped with autotransformer impedance matching systems.

SELECTORS:

High-quality selectors and components ensure zone fidelity, even with all outputs engaged simultaneously.

AUTOTRANSFORMERS:

Impedance match at each output for best results

FORMAT:

Standard 17-inch wide format integrates easily with other equipment.



CONTROLS:

Convenient controls for volume, source and position keep the music when, where and how you like it.



AT4V, 4-way with volume



AT6V, 6-way with volume



AT4, 4-way



AT6, 6-way

Model	Type	Power Handling RMS	Volume Attenuation	Source Selection	Individual On / Off	Terminal Gauge	Weight Kg / lbs	Dimensions (H x W x D) mm / inches
AT4V	With Volume	100 w	9 step	2	Yes	22 / 14	3.6 / 8.0	63 x 431 x 149 / 2.5 x 17.0 x 5.9
AT6V	With Volume	100 w	9 step	2	Yes	22 / 14	4.2 / 9.4	63 x 431 x 149 / 2.5 x 17.0 x 5.9
AT4	Without Volume	100 w	N/A	2	Yes	22 / 14	3.4 / 7.5	63 x 431 x 149 / 2.5 x 17.0 x 5.9
AT6	Without Volume	100 w	N/A	2	Yes	22 / 14	4.1 / 9.0	63 x 431 x 149 / 2.5 x 17.0 x 5.9